

LINE MONITOR AMPLIFIER

MP-5010



[Zoom](#) |

[Print](#) |

[Leaflet](#) | [Drawing](#) | [Manual](#) |

Features

SECTION.

- * Permissible monitor for 10pcs-power Amplifier output by monitor selector.
- * Level adjustment of input level for each monitor.
- * Permissible signal input 1V-100V(US 1V-70V)according to setting for monitor input.
- * LED meter per monitor input.
- * Two way monitors by speaker.
- * No problem by potential difference between product unbalanced. Due to balanced input circuit.
- * AUX input for monitor of pre AMP out.

▶ Technical Specifications

Relate Monitor	Speaker monitor 2W max
Input Sensitivity / Impedance	1V – 70V / 10Kohms bal (US) 1V – 100V / 10Kohms bal (EU)
Frequency Response	Less than -3dB 100Hz – 20KHz
T.H.D (1KHz)	Less than 0.3%
Power Consumption	12W All Operation
Power Source	110-240VAC 50/60Hz, and 24VDC
Dimensions (W x H x D) mm/inch	483 x 44 x 120 & 19.0 x 1.7 x 5.0
Weight (kg/lbs)	4.7/10.4

OFFICE & FACTORY : 1115-34 Hwagok-Dong, Kangseo-ku, Seoul, Korea.

www.suhyoon.co.kr **E-MAIL**: suhyoon@suhyoon.co.kr